

Lecture 6

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec,

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s)$$

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s) = \cos(\omega n + \phi)$$

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s) = \cos(\omega n + \phi) ,$$

where $\omega = \Omega T_s$.

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s) = \cos(\omega n + \phi) ,$$

where $\omega = \Omega T_s$.

- ▶ Two different sampling periods T_s and T'_s may result in the same *effective* ω .

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s) = \cos(\omega n + \phi) ,$$

where $\omega = \Omega T_s$.

- ▶ Two different sampling periods T_s and T'_s may result in the same *effective* ω . This happens when

$$T'_s = \pm T_s + kT$$

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s) = \cos(\omega n + \phi) ,$$

where $\omega = \Omega T_s$.

- ▶ Two different sampling periods T_s and T'_s may result in the same *effective* ω . This happens when

$$T'_s = \pm T_s + kT$$

($T = 2\pi/\Omega$, period in continuous time.)

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s) = \cos(\omega n + \phi) ,$$

where $\omega = \Omega T_s$.

- ▶ Two different sampling periods T_s and T'_s may result in the same *effective* ω . This happens when

$$T'_s = \pm T_s + kT$$

($T = 2\pi/\Omega$, period in continuous time.)

- ▶ *Aliasing*: Two *different* sinusoids in continuous time, with frequencies Ω and Ω'

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s) = \cos(\omega n + \phi) ,$$

where $\omega = \Omega T_s$.

- ▶ Two different sampling periods T_s and T'_s may result in the same *effective* ω . This happens when

$$T'_s = \pm T_s + kT$$

($T = 2\pi/\Omega$, period in continuous time.)

- ▶ *Aliasing*: Two *different* sinusoids in continuous time, with frequencies Ω and Ω' , may produce sample sequences having the *same* effective frequency ω

Lecture 6

- ▶ $x(t) = \cos(\Omega t + \phi)$, when sampled at rate $f_s = 1/T_s$ samples/sec, produces

$$x[n] = x(nT_s) = \cos(\omega n + \phi) ,$$

where $\omega = \Omega T_s$.

- ▶ Two different sampling periods T_s and T'_s may result in the same *effective* ω . This happens when

$$T'_s = \pm T_s + kT$$

($T = 2\pi/\Omega$, period in continuous time.)

- ▶ *Aliasing*: Two *different* sinusoids in continuous time, with frequencies Ω and Ω' , may produce sample sequences having the *same* effective frequency ω when sampled at the *same* instants nT_s .