

1. Assume that $v(n)$ is a real-valued zero-mean white Gaussian noise with $\sigma_v^2 = 1$, $x(n)$ and $y(n)$ are generated by the equations

$$x(n) = 0.5x(n - 1) + v(n),$$

$$y(n) = x(n - 1) + x(n).$$

- (a) Find the power spectrum of sequence $x(n)$, and its power.
- (b) Find the power spectrum of sequence $y(n)$, and its power.
- (c) Calculate $r_y(k)$ for $k = 0, 1, 2, 3$.

Assume now we don't know the real model of the signal, and we want to estimate its power spectrum from $r_y(k)$ obtained in part (c). Estimate power spectrum using the following methods:

- (d) ARMA(1,1) spectral estimation.
- (e) AR(2) spectral estimation.
- (f) Maximum entropy spectral estimation with order 2.
- (g) Minimum variance spectral estimation with order 1.

2. Show that the periodogram spectrum estimator will result in biased results if an N -point rectangular window is applied, i.e., $P_{PER}(\omega) = \frac{1}{N} |\sum_{n=0}^{N-1} x(n)e^{-j\omega n}|^2$ is biased.

3. Consider a wide-sense stationary process consisting of p distinct complex sinusoids in white noise with variance σ^2 , i.e.

$$x(n) = \left[\sum_{i=1}^p A_i e^{-j(n\omega_i + \phi_i)} \right] + v(n)$$

where A_i and ϕ_i are uncorrelated, and ϕ_i is a uniformly distributed random variable in $[0, 2\pi)$.

- (a) Find the autocorrelation function $r(k) = E[x(n)x(n - k)]$.
- (b) Find the $(p + 1) \times (p + 1)$ correlation matrix R .

4. Consider a random process

$$x(n) = A \exp[j(n\omega_0 + \phi)] + \alpha_0 v[n] + \alpha_1 v[n - 1],$$

where $\{v[n]\}$ is a white noise process with zero mean and variance σ_v^2 . The phase ϕ is uniformly distributed over $[0, 2\pi)$ and uncorrelated with $v[n]$; and A, ω_0, α_0 , and α_1 are real-valued constants.

(a) Find the autocorrelation function for $\{x[n]\}$ in terms of $A, \omega_0, \alpha_0, \alpha_1$, and σ_v^2 . Your solution should provide all the necessary steps and justifications.

(b) Consider the process in $\{x[n]\}$ for the case of $\alpha_0 = 1$ and $\alpha_1 = 0$. First, determine the eigen values of an $M \times M$ correlation matrix of the $\{x[n]\}$ process. Next, suppose we have observed N

samples, $x[0], x[1], \dots, x[N - 1]$. Use equation, diagram, and concise words to describe the average periodogram method for estimating method for estimating the power spectrum density of the $\{x[n]\}$ process.

5. Assume the signal $x(n) = a\cos(\omega n + \phi) + v(n)$, where a is an unknown constant, $v(n)$ is a white Gaussian noise independent of the sinusoid. Suppose we know the autocorrelation coefficients $r(0) = 3$, $r(1) = \sqrt{2}$, and $r(2) = 0$, determine the frequency of the sinusoid ω and the noise power σ_v^2 .